

**Main page:** [Cisco Unified Presence, Release 7.x](#)

## Contents

- [1 Previous Topic](#)
- [2 Before You Begin](#)
- [3 Procedure](#)
- [4 Related Topics](#)

### Previous Topic

- [How to Configure Conferencing Servers and Profiles for Cisco Unified Personal Communicator](#)

Using Cisco Unified Communications Manager Administration, you can enable merged conference calls (three or more parties) with audio and video support for Cisco Unified Personal Communicator softphone users. Any participant in the conference call can merge other participants into the conference.

### Before You Begin

- Install a supported release of the video conferencing server.
- Obtain the MAC address of the video conference bridge.

### Procedure

1. Perform the following configuration on Cisco Unified Communications Manager:

Task	Menu path
Configure the videoconference bridge.	<b>Cisco Unified CM Administration &gt; Media Resources &gt; Conference Bridge</b>
Create a media resource group list	<b>Cisco Unified CM Administration &gt; Media Resources &gt; Media Resource Group List</b>
Add the videoconference bridge to the media resource group list	
Create a media resource group	<b>Cisco Unified CM Administration &gt; Media Resources &gt; Media Resource Group</b>
Add a media resource to the media resource group	

2. (Optional) To enable any participant to add more participants the conference, perform the following steps:

- ◇ Select **Cisco Unified CM Administration > System > Service Parameters**.
- ◇ Select the Cisco Unified Communications Manager server and service.
- ◇ Set Advanced Ad Hoc Conference Enabled to **True** in the Clusterwide Parameter (Feature - Conference) section.

3. Associate the phone with the new media resource group list:

- ◇ Select **Cisco Unified CM Administration > Device > Phone**.
- ◇ Under Search Options, search for the directory number of the phone, and when it is found, select the device name.
- ◇ In the Phone Configuration window in the Device Information section, find the Media Resource Group List, and select the media resource group list that you just configured.
- ◇ Select **Enabled** for Video Capabilities in the Product Specific Configuration Layout section.
- ◇ Select **Save**.
- ◇ Select **Reset**.

#### Related Topics

- For details about the Cisco Unified Video Conferencing server installation, see the product installation guide:

[http://www.cisco.com/en/US/products/hw/video/ps1870/tsd\\_products\\_support\\_series\\_home.html](http://www.cisco.com/en/US/products/hw/video/ps1870/tsd_products_support_series_home.html)

- For details about supported Cisco Unified Video Conferencing releases, see the Cisco Unified Personal Communicator release notes:

[http://www.cisco.com/en/US/products/ps6844/prod\\_release\\_notes\\_list.html](http://www.cisco.com/en/US/products/ps6844/prod_release_notes_list.html)

- For detailed Cisco Unified Communications Manager configuration instructions, use the Cisco Unified Communications Manager Administration online help or the *Cisco Unified Communications Manager Administration Guide*:

[http://www.cisco.com/en/US/products/sw/voicesw/ps556/prod\\_maintenance\\_guides\\_list.html](http://www.cisco.com/en/US/products/sw/voicesw/ps556/prod_maintenance_guides_list.html)

- [Creating a Softphone Device for Each Cisco Unified Personal Communicator User](#)
- [Configuring Users for Point-to-Point Video Calls and for Multipoint Video Conferencing](#)
- [Getting More Information](#)