

Cannot make configuration changes in HA cluster

Problem Summary	Unable to make configuration changes in a high availability cluster when one node is down.
Error Message	None.
Possible Cause	If one node is down, configuration changes cannot be made because the changes are written to both configuration datastores at the same time.
Recommended Action	Do the following: <ol style="list-style-type: none">1. Make sure that the Publisher is the active node. If it is not, use Cisco Unified CCX Administration to make it the active node for all datastores.2. Deactivate CDS and HDS for the inactive node using the Component Activation link.
Release	Release 7.0(1)
Associated CDETS #	None.