

Main page: [Cisco Unified MeetingPlace, Release 7.0](#)

Up one level: [Reference Information](#)

Note: This report provides a separate entry for each Device used by a meeting participant

Table: Export Data Specifications-Meeting Participant Join Leave Information

Field	Description	Size and Type of Value
PartID	See PartID .	0 to 17 ASCII text characters
UserID	User ID of the meeting participant.	1 to 30 alphanumeric characters
ConfNum	See ConfNum .	1 to 9 numeric characters
MeetingID	Meeting ID.	
gmStartDate	Date on which the user joined the meeting.	MM/DD/YYYY
gmStartTime	Time at which the user joined the meeting.	HH:MM:SS AM/PM
gmEndDate	Date on which the user left the meeting.	MM/DD/YYYY
gmEndTime	Time at which the user left the meeting.	HH:MM:SS AM/PM
Device	Device identifier or port number: <ul style="list-style-type: none"> • 0 to 1151-voice port • 4080-MeetingPlace Conference Manager • 4081-Cisco Unified MeetingPlace Web Conferencing • 4082-Share pod in web meeting • 4084-Cisco Unified MeetingPlace Video 	<ul style="list-style-type: none"> • 0 to 1151 • 4080 to 4084
nIncDigits	Number of DNIS digits that were received from the PBX.	An unsigned integer
IncDigits	String of DNIS digits received from the PBX.	Numerical string of up to 24 digits
AttachmentID	Not supported.	Not supported.
nANIDigits	Number of alpha-numeric characters in the display name, or the number of ANI digits that were received from the PBX. The display name takes precedence; if not present, the ANI value is used.	An unsigned integer
ANIDigits	Alpha-numeric characters in the display name, or the string of ANI digits received from the PBX. The display name takes precedence; if not present, the ANI value is used.	Alpha-numeric string of up to 24 digits

Related Topics

- [Running Reports and Exporting Data from Cisco Unified MeetingPlace](#)