

Main page: [Cisco Unified MeetingPlace Express, Release 2.x](#)

Previous page: [Page References](#)

This page is used to export information about meeting participants who joined or left a Cisco Unified MeetingPlace Express meeting during a specified range of dates. Topics in this section include:

- [Field Reference: Meeting Participant Join Leave Information](#)
- [Output Fields of the Meeting Participant Join Leave Information Page](#)

Field Reference: Meeting Participant Join Leave Information

Table: Fields on the Meeting Participant Join Leave Information Page

| Field | Description | Value |
|----------------------------|--|---|
| Destination | Destination of the exported information. For descriptions, restrictions, and recommendations for each option, see the How To Export Data . | Screen/File/Printer Default: Screen |
| Include field header names | Whether or not to include the field header names in the exported file. | No/Yes Default: Yes |
| Start date | Earliest date for which you want to export meeting participant join leave information. | Format: mm/dd/yyyy Default: yesterday's date |
| End date | Latest date for which you want to export meeting participant join leave information. | Format: mm/dd/yyyy Default: today's date |

Output Fields of the Meeting Participant Join Leave Information Page

| Field | Description |
|-----------|--|
| PartID | Meeting participant ID. |
| UserID | Username used to log in to Cisco Unified MeetingPlace Express from a workstation (not from a phone). |
| ConfNum | Unique number used by the local audio mixer to identify the voice meeting. This value is different from the meeting ID displayed to end users. |
| MeetingID | |

| | |
|--------------|--|
| | Meeting ID, which uniquely identifies the meeting. If you do not specify one, the system automatically assigns your phone number as the meeting ID. |
| gmStartDate | The date that the user entered the meeting. |
| gmStartTime | The time that the user entered the meeting. |
| gmEndDate | The date that the user left the meeting. |
| gmEndTime | The time that the user left the meeting. |
| Device | Device and port number used to join the meeting: <ul style="list-style-type: none"> • 4081-4082: web port • all other values: voice port |
| nIncDigits | The number of DNIS digits that were received from the PBX. |
| IncDigits | The actual string of DNIS digits received from the PBX. Can be up to 24 digits. |
| AttachmentID | Not supported. |
| nANIDigits | The number of ANI digits that were received from the PBX. |
| ANIDigits | The actual string of ANI digits received from the PBX. Can be up to 24 digits. |