

Main page: [Cisco Unified MeetingPlace Express, Release 2.x](#)

Previous page: [Page References](#)

This page is used to export information about failed attempts to schedule meetings during a specified range of dates.

- [Field Reference: Scheduling Failures Information](#)
- [Output Fields of the Scheduling Failures Information Page](#)
- [Failure Codes of the Scheduling Failures Information Page](#)

Contents

- [1 Field Reference: Scheduling Failures Information](#)
 - ◆ [1.1 Table: Fields on the Scheduling Failures Information Page](#)
- [2 Output Fields of the Scheduling Failures Information Page](#)
- [3 Failure Codes of the Scheduling Failures Information Page](#)

Field Reference: Scheduling Failures Information

Table: Fields on the Scheduling Failures Information Page

Field	Description	Value
Destination	Destination of the exported information. For descriptions, restrictions, and recommendations for each option, see the How To Export Data .	Screen/File/Printer Default: Screen
Include field header names	Whether to include the field header names in the exported file.	No/Yes Default: Yes
Start date	Earliest date for which you want to export scheduling failures information.	<ul style="list-style-type: none"> • Date in the format MM/DD/YYYY • Click ... to choose a date. Default: yesterday's date
End date	Latest date for which you want to export scheduling failures information.	<ul style="list-style-type: none"> • Date in the format MM/DD/YYYY

		<ul style="list-style-type: none"> • Click ... to choose a date.
		Default: today's date

Output Fields of the Scheduling Failures Information Page

Field	Description
SchedulerUid	The username (used to log in to Cisco Unified MeetingPlace Express from a workstation, not from a phone) of the person who scheduled the meeting.
SchedulingTime	The date and time when the user tried to schedule the meeting.
MtgStartTime	The date and start time for the meeting that the user was trying to schedule.
DialableConfID	Unique number used by the local audio mixer to identify the voice meeting. This value is different from the meeting ID displayed to end users.
NumOfPortsRqsted	The number of ports requested for the failed meeting.
MtgLenthInMin	The length, in minutes, of the failed meeting.
UnitNo	<i>Not supported.</i>
SiteNo	<i>Not supported.</i>
SlotNo	<i>Not supported.</i>
FailCode	The failure code that describes why the meeting could not be scheduled. See Table: Exception Codes for information about the failure codes.
fSchedOnHomeServerOnly	Whether the user's profile is set to schedule meetings on the home server only.
fSchedOnHomeSiteOnly	<i>Not supported.</i>
ErrorString	A text string message that is displayed to the user. This message corresponds to the FailCode .
FailSeqNum	Tracks multiple failure attempts for the same meeting.
UniqueConfNum	Unique conference number assigned to this meeting after it was successfully scheduled. This is 0 for meetings that are not scheduled successfully.

Failure Codes of the Scheduling Failures Information Page

Field	Description
5155	Server did not extend meeting because of one of these reasons: <ul style="list-style-type: none"> • Less than two participants were in the voice and web conferencing sessions. • The meeting was extended to more than 24 hours. • The Extend Meeting parameter was set to 0 minutes.
5209	The conference was terminated.
5122	Generic code for any error found from internal reservation mechanism.
5154	The server cannot commit the extensions because of a failure to save the extension record to the database.

5129	Original resource reservation cannot be found.
131198	Failed to extend because of lack of voice ports.
131199	Failed to extend because of lack of recording space.
131262	Failed to extend because of meeting ID conflict.
131158	One person remains in the conference.
131159	Conference was extended more than 24 hours.