

[Cisco Unified MeetingPlace Release 6.1](#) > [Cisco Unified MeetingPlace Audio Server](#) > [Maintaining > Creating, Uploading, and Deleting Custom Voice Prompts](#)

After you have recorded a custom voice prompt, you may need to delete it.

#### To Delete Custom Voice Prompts

1. Open a telnet session into the target Cisco Unified MeetingPlace 8100 series and log in as a technician.
2. Once you are in the telnet session, change to the superuser level. You need the password of the day (POD) to log in as a superuser. Contact Cisco TAC for the POD.
3. Run *bnrprompt -x <prompt number>* to delete the custom voice prompt. The screen displays the following:

```
csc$ bnrprompt -x 304
Logging in to cp ....
... Done ....
Delete standard custom prompt 304
Deleted file standard prompt 304
No abbreviated prompt exists 304
Removed this custom prompt 304
FINISHED: Delete Custom Recorded (CR) Prompts complete!
```

4. Run *bnrprompt -l* to verify that the custom voice prompt was removed. The screen displays the following:

```
csc$ bnrprompt -l
Starting English (US)...
... Done with English (US) -> no custom prompts exist
(1776/1777)
FINISHED: List Custom Recorded (CR) Prompts complete!
```