

**Main page:** [Cisco Unified MeetingPlace, Release 8.0](#)

**Back to:** [Installation, Upgrade and Migration](#)

**Back to:** [Reference Information](#)

- [RS-232 9-Pin D-Type Serial Port](#)
- [9-Pin Serial Port Terminal Cable](#)
- [RJ-45 8-Pin IP Network Port](#)

## Contents

- [1 RS-232 9-Pin D-Type Serial Port](#)
  - ◆ [1.1 Table: RS-232 9-Pin D-Type Serial Port Pin-Out](#)
- [2 9-Pin Serial Port Terminal Cable](#)
  - ◆ [2.1 Table: RS-232 Terminal Cable Pin-to-Pin Configuration](#)
- [3 RJ-45 8-Pin IP Network Port](#)
  - ◆ [3.1 Table: Pin-Out Configuration of the RJ-45 8-Pin IP Network Port](#)

## RS-232 9-Pin D-Type Serial Port

[Table: RS-232 9-Pin D-Type Serial Port Pin-Out](#) describes the Cisco Unified MeetingPlace Hardware Media Server RS-232 9-pin D-type serial port pin-out configuration.

**Table: RS-232 9-Pin D-Type Serial Port Pin-Out**

Pin	Function	I/O
1	NC	
2	RXD	Input
3	TXD	Output
4	NC	
5	GND	
6	NC	
7	NC	
8	NC	
9	NC	

## 9-Pin Serial Port Terminal Cable

Table: RS-232 Terminal Cable Pin-to-Pin Configuration describes the pin-to-pin configuration of the RS-232 terminal cable provided with the Cisco Unified MeetingPlace Hardware Media Server.

**Table: RS-232 Terminal Cable Pin-to-Pin Configuration**

To Chassis (DB-9 Male)	Function	To PC Terminal (DB-9 Female)
2	TXD	3
3	RXD	2
5	GND	5

## RJ-45 8-Pin IP Network Port

Table: Pin-Out Configuration of the RJ-45 8-Pin IP Network Port describes the pin-out configuration of the RJ-45 8-pin IP network port.

**Table: Pin-Out Configuration of the RJ-45 8-Pin IP Network Port**

Component	Pin	Function	I/O
Audio	1	TXRX0+	Bidirectional data pair 0
	2	TXRX0-	Bidirectional data pair 0
	3	TXRX1+	Bidirectional data pair 1
	4	TXRX2+	Bidirectional data pair 2
	5	TXRX2-	Bidirectional data pair 2
	6	TXRX1-	Bidirectional data pair 1
	7	TXRX3+	Bidirectional data pair 3
	8	TXRX3-	Bidirectional data pair 3
Video	1	TXD+	Output
	2	TXD+	Output
	3	RXD+	Input
	4	NC	
	5	NC	
	6	RXD-	Input
	7	NC	
	8	NC	