

**Main page:** [Cisco Unified Presence, Release 7.x](#)

## Contents

- [1 Previous Topic](#)
- [2 Before You Begin](#)
- [3 Procedure](#)
- [4 Troubleshooting Tips](#)
- [5 Related Topics](#)
- [6 What To Do Next](#)

### Previous Topic

- [Configuring Cisco Unified Presence Release 7.x with Microsoft Exchange Server](#)

By default, the Presence Engine listens for incoming notifications from the Exchange server on UDP port 50020. This topic only applies if you want to use another port for any reason specific to your network configuration.

### Before You Begin

If you change from the default port, make sure that the replacement port you assign is not already in use.

### Procedure

1. Select **Cisco Unified Presence Administration > System > Service Parameters**.
2. Select the Cisco Unified Presence server from the Server menu.
3. Select **Cisco UP Presence Engine (Active)** from the Service menu.
4. Edit the Parameter Value field in the Presence Engine Configuration section. By default this parameter is 50020.
5. Select **Save**.

### Troubleshooting Tips

If you change from the default port, the Presence Engine will continue to use the existing calendar information for users, (including the number of meetings and the start and end times) until such time as the Exchange subscription for the user is renewed. It may take up to an hour for the Presence Engine to receive notifications that a user's calendar has changed.

**Related Topics**

- [Getting More Information](#)
- [Known Issues with Microsoft Exchange Server Integration](#)

**What To Do Next**

- [How to Configure Security between Cisco Unified Presence and the Microsoft Exchange Server](#)