

Main page: [Cisco Unified Presence, Release 7.x](#)

Contents

- [1 Previous Topic](#)
- [2 System Operations](#)
- [3 Shutting Down the System](#)
 - ◆ [3.1 Procedure](#)
 - ◆ [3.2 Troubleshooting Tips](#)
 - ◆ [3.3 Related Topics](#)
 - ◆ [3.4 What To Do Next](#)
- [4 How to Work with Disk Partitions](#)
 - ◆ [4.1 Reverting a Cisco Unified Presence Node to a Previous Version](#)
 - ◇ [4.1.1 Before You Begin](#)
 - ◇ [4.1.2 Procedure](#)
 - ◇ [4.1.3 Troubleshooting Tips](#)
 - ◇ [4.1.4 Related Topics](#)
 - ◆ [4.2 Restarting the Current Version](#)
 - ◇ [4.2.1 Before You Begin](#)
 - ◇ [4.2.2 Procedure](#)
 - ◇ [4.2.3 Troubleshooting Tips](#)
 - ◇ [4.2.4 Related Topics](#)

Previous Topic

- [Cisco Unified Operating System Administration for Cisco Unified Presence](#)

- [System Operations](#)
- [Shutting Down the System](#)
- [How to Work with Disk Partitions](#)

System Operations

You may need to choose from the following options to shut down or restart the system:

- Shutdown-Stops all running software and shuts down the server.
- Switch Versions-Switches the active and inactive disk partitions and restarts the system. You normally select this option after the inactive partition has been updated and you want to start running a newer software version.
- Restart-Restarts the system without switching partitions.

Note: To power down the server, press the power button. Note, however, that this action may lead to file system corruption and is not recommended.

Shutting Down the System

Procedure

1. Log in to Cisco Unified Operating System Administration.
2. Select **Settings > Version**.
3. Perform one of the following actions:
 1. Click **Shutdown** to halt all processes and shut down the system.
 2. Click **Cancel** to stop the operation.

Troubleshooting Tips

The hardware does not power down automatically. If you press the power button on the server, the system will immediately shut down.

Related Topics

- [Getting More Information](#)

What To Do Next

[How to Work with Disk Partitions](#)

How to Work with Disk Partitions

- [Reverting a Cisco Unified Presence Node to a Previous Version](#)
- [Restarting the Current Version](#)

Reverting a Cisco Unified Presence Node to a Previous Version

When you are upgrading to a newer software version and when you need to fall back to an earlier software version, you can shut down the system that is running on the active disk partition and then automatically restart the system using the software version on the inactive partition. The software version running on both the active and inactive partitions is indicated.

Caution! This procedure causes the system to restart and become temporarily out of service.

Before You Begin

Upgrade the database on the active partition. The database on the inactive partition does not get updated. If you make changes to the database after an upgrade, you must repeat those changes after switching the partition.

Procedure

1. Log in to Cisco Unified Operating System Administration.
2. Select **Settings > Version**.
3. Perform one of the following actions:
4. Click **Switch Versions** to switch versions and restart the system.
5. Click **Cancel** to stop the operation.

Troubleshooting Tips

- If you click **Switch Versions**, the system restarts, and the partition that is currently inactive becomes active.
- After you verify that you want to restart the system, the system restarts, which might take up to 15 minutes.

Related Topics

- [Upgrading Software in Cisco Unified Operating System](#)
- [Getting More Information](#)

Restarting the Current Version

You can restart the system on the current partition without switching versions.

Caution! This procedure causes the system to restart and become temporarily out of service.

Before You Begin

Shut down the system on which the active version is running.

Procedure

1. Log in to Cisco Unified Operating System Administration.
2. Select **Settings > Version**.
3. Perform one of the following actions:

Before You Begin

4. Click **Restart** to restart the system.
5. Click **Cancel** to stop the operation.

Troubleshooting Tips

If you click **Restart**, the system restarts on the current partition without switching versions.

Related Topics

- [Shutting Down the System](#)
- [Getting More Information](#)