

Links to Other API pages: [Cisco Unity Connection APIs](#)

CUPI Guide Contents
API Overview
Index of All CUPI Documentation

Contents

- [1 User Password and PIN Settings API](#)
 - ◆ [1.1 Listing User PIN Settings](#)
 - ◆ [1.2 Listing User Password Settings](#)
 - ◆ [1.3 Update Password/PIN Settings](#)
 - ◆ [1.4 Unlock Password/PIN Settings](#)
 - ◆ [1.5 To Unlock Password](#)
 - ◆ [1.6 Change Password/PIN](#)
 - ◆ [1.7 Explanation of Data Fields](#)

User Password and PIN Settings API

Listing User PIN Settings

GET https://<Connection-server>/vmrest/users/<user-objectid>/credential/pin

The following is the response from the above *GET* request and the actual response will depend upon the information given by you:

```
<Credential>
  <URI>/vmrest/users/9375d893-c8eb-437b-90bf-7de4b1d0c3e8/credential/pin</URI>
  <UserObjectId>9375d893-c8eb-437b-90bf-7de4b1d0c3e8</UserObjectId>
  <CredentialType>4</CredentialType>
  <Credentials/>
  <IsPrimary>>false</IsPrimary>
  <CantChange>>false</CantChange>
  <DoesntExpire>>true</DoesntExpire>
  <TimeChanged>2013-03-05 11:24:33.344</TimeChanged>
  <HackCount>5</HackCount>
  <Locked>>true</Locked>
  <TimeLastHack>2013-03-11 10:23:30.581</TimeLastHack>
  <TimeLockout>2013-03-05 11:24:33.344</TimeLockout>
  <Alias>Texoma</Alias>
  <CredMustChange>>true</CredMustChange>
  <CredentialPolicyObjectId>a97ff291-8e60-475a-b7ee-e956ae83a730</CredentialPolicyObjectId>
  <Hacked>>false</Hacked>
  <ObjectId>3f6f1cb0-3b00-45b5-91fd-d8553737eec7</ObjectId>
  <EncryptionType>3</EncryptionType>
```

Cisco_Unity_Connection_Provisioning_Interface_(CUPI)_API_--_User_Password_PIN_Settings

</Credential>

Response Code: 200

Listing User Password Settings

GET https://<Connection-server>/vmrest/users/<user-objectid>/credential/password

The following is the response from the above *GET* request and the actual response will depend upon the information given by you:

```
<Credential>
  <URI>/vmrest/users/9375d893-c8eb-437b-90bf-7de4b1d0c3e8/credential/password</URI>
  <UserObjectId>9375d893-c8eb-437b-90bf-7de4b1d0c3e8</UserObjectId>
  <CredentialType>3</CredentialType>
  <Credentials/>
  <IsPrimary>>false</IsPrimary>
  <CantChange>>false</CantChange>
  <DoesntExpire>>true</DoesntExpire>
  <TimeChanged>2013-03-05 11:24:33.344</TimeChanged>
  <HackCount>5</HackCount>
  <Locked>>true</Locked>
  <TimeLastHack>2013-03-11 10:23:30.581</TimeLastHack>
  <TimeLockout>2013-03-05 11:24:33.344</TimeLockout>
  <Alias>Texoma</Alias>
  <CredMustChange>>true</CredMustChange>
  <CredentialPolicyObjectId>a97ff291-8e60-475a-b7ee-e956ae83a730</CredentialPolicyObjectId>
  <Hacked>>false</Hacked>
  <ObjectId>3f6f1cb0-3b00-45b5-91fd-d8553737eec7</ObjectId>
  <EncryptionType>3</EncryptionType>
</Credential>
```

Response Code: 200

JSON Example

```
GET https://<Connection-server>/vmrest/users/<user-objectid>/credential/password
Accept: application/json
Content-type: application/json
Connection: keep-alive
```

The following is the response from the above *GET* request and the actual response will depend upon the information given by you:

```
{
  ?URI?: ?/vmrest/users/9375d893-c8eb-437b-90bf-7de4b1d0c3e8/credential/password?
  ?UserObjectId?: ?9375d893-c8eb-437b-90bf-7de4b1d0c3e8?
  ?CredentialType?: ?3?
  ?Credentials?
  ?IsPrimary?: ?false?
  ?CantChange?: ?false?
  ?DoesntExpire?: ?true?
  ?TimeChanged?: ?2013-03-05 11:24:33.344?
  ?HackCount?: ?5?
  ?Locked?: ?true?
  ?TimeLastHack?: ?2013-03-11 10:23:30.581?
  ?TimeLockout?: ?2013-03-05 11:24:33.344?
  ?Alias?: ?Texoma?
  ?CredMustChange?: ?true?
  ?CredentialPolicyObjectId?: ?a97ff291-8e60-475a-b7ee-e956ae83a730?
```

Cisco_Unity_Connection_Provisioning_Interface_(CUPI)_API_--_User_Password_PIN_Settings

```
?Hacked?: ?false?  
?ObjectId?: ?3f6f1cb0-3b00-45b5-91fd-d8553737eec7?  
?EncryptionType?: ?3?  
}
```

Response Code: 200

Update Password/PIN Settings

For PIN:

```
PUT https://<Connection-server>/vmrest/users/<user-objectid>/credential/pin
```

For Password:

```
PUT https://<Connection-server>/vmrest/users/<user-objectid>/credential/password
```

```
<Credential>  
  <Locked>>false</Locked>  
  <DoesntExpire>>true</DoesntExpire>  
  <CredMustChange>>true</CredMustChange>  
  <CredentialPolicyObjectId>43e16996-57c6-46c4-86c0-f37d2edf0385</CredentialPolicyObjectId>  
</Credential>
```

The following is the response from the above *PUT* request and the actual response will depend upon the information given by you:

Response Code: 204

Unlock Password/PIN Settings

A user's PIN is the password that a user must enter over the phone to sign into their mailbox to listen or send new messages by phone. To change a user's PIN you need the object ID of the user. A user's password is the web application password that is required to interact with web applications, such as the Cisco PCA or the Inbox applications.

For Password:

```
PUT https://<Connection-server>/vmrest/users/<user-objectid>/credential/password
```

For PIN:

```
PUT https://<Connection-server>/vmrest/users/<user-objectid>/credential/pin
```

```
<Credential>  
  <HackCount>0</HackCount>  
  <TimeHacked></TimeHacked>  
</Credential>
```

The following is the response from the above *PUT* request and the actual response will depend upon the information given by you:

Response Code: 204

JSON Example:

To Unlock Password

```
PUT https://<Connection-server>/vmrest/users/<user-objectid>/credential/password
Accept: application/json
Content-type: application/json
Connection: keep-alive
Response Body:
{
  "HackCount": "0",
  "TimeHacked": ""
}
```

The following is the response from the above *PUT* request and the actual response will depend upon the information given by you:

Response Code: 204

Change Password/PIN

For Password: PUT

```
https://<Connection-server>/vmrest/users/<user-objectid>/credential/password
```

For PIN:

```
PUT https://<Connection-server>/vmrest/users/<user-objectid>/credential/pin
```

```
<Credential>
  <Credentials>ciscfo1234</Credentials>
</Credential>
```

The following is the response from the above *PUT* request and the actual response will depend upon the information given by you:

Response Code: 204

JSON Example:

To Update PIN

```
PUT https://<Connection-server>/vmrest/users/<user-objectid>/credential/pin
Accept: application/json
Content-type: application/json
Connection: keep-alive
Response Body:
{
  "Credentials": "cisco1234"
}
```

The following is the response from the above *PUT* request and the actual response will depend upon the information given by you:

Response Code: 204

Explanation of Data Fields

Field Name	Data Type	Operation	Description
Locked	Boolean	Read/Write	<p>A flag indicating whether access to the user account associated with this set of credentials is locked.</p> <p>Possible values:</p> <ul style="list-style-type: none"> • true • false <p>Default value: false</p>
CantChange	Boolean	Read/Write	<p>A flag indicating whether the user can set this credential.</p> <p>Possible values:</p> <ul style="list-style-type: none"> • false: User can change credential • true: User cannot change credential <p>Default Value: false</p>
CredMustChange	Boolean	Read/Write	<p>A flag indicating whether the user must change their credentials (PIN or password) at the next login.</p> <p>Possible values:</p> <ul style="list-style-type: none"> • true • false <p>Default Value :true</p>
DoesntExpire	Boolean	Read/Write	<p>A flag indicating whether this user credential will expire, and therefore the user must change the credential periodically. However, if the credential does not expire (value = "true"), the user still may change the credential (if allowed by CantChange).</p> <p>Possible values:</p> <ul style="list-style-type: none"> • true • false <p>Default value: false</p>
CredentialPolicyObjectId	String(36)	Read/Write	<p>The unique identifier of the CredentialPolicy object that is associated with this credential. Value for this parameter can be fetched from the objectId parameter. Response of the following URI: GET:<a href="https://<connection-server>/vmrest/credentialpolicies">https://<connection-server>/vmrest/credentialpolicies.</p>
TimeChanged	datetime(8)	Read/Write	<p>The date and time when the credentials were last changed. The date and time is recorded in this column whenever a</p>

Cisco_Unity_Connection_Provisioning_Interface_(CUPI)_API_--_User_Password_PIN_Settings

			user credential is created or changed.
HackCount	Integer(4)	Read/Write	The number of logon attempted that failed due to invalid credentials. The Unity system or external authentication provider determined that the credentials supplied as part of a user logon attempt were invalid. Default value: 0
TimeLastHack	datetime(8)	Read/Write	The date and time of the last logon attempt with an invalid user credential.
TimeLockout	datetime(8)	Read/Write	The date and time that the credential was locked by an administrator.
TimeHacked	datetime(8)	Read/Write	The date and time that the credential was locked due to too many hacks. The date and time is recorded in this column whenever a user credential is locked due to too many hacks based on the credential policy.
ObjectId	String (36)	Read Only	Unique identifier for the password/pin
Credentials	String(256)	Read/Write	The PIN or password, for a user. The credentials are stored in an encrypted format.
Alias	String(64)	Read/Write	A unique text name of the user.
Hacked	Boolean	Read/Write	A flag indicating whether access to the user account associated with this set of credentials is locked due too many hack attempts. Possible Values: <ul style="list-style-type: none">• true• false Default Value: false
EncryptionType	Integer	Read/Write	Type of encryption that was used to generate the credentials. Possible values:(0-5) <ul style="list-style-type: none">• UNKNOWN: 0• HASH_MD5: 1• HASH_SHA1: 2• HASH_IMS: 3• REVERSIBLE: 4• NONE: 5 Default Value: 0
CredentialType	CredentialType	Read/Write	The type of credential such as password, PIN, Windows or Domino credential. <ul style="list-style-type: none">• 4- for PIN

Cisco_Unity_Connection_Provisioning_Interface_(CUPI)_API_--_User_Password_PIN_Settings

			• 3- for Password
--	--	--	-------------------