

Database no longer accepts data

Problem Summary	The Cisco MediaSense Enterprise Replication Smart Blob (Binary Large Object) space, referred to as ora_ersb, cannot accept any more data.
Error Message	Informix log: 08/27/11 19:20:56 CDR QUEUER: Send Queue space is FULL - waiting for space in CDR_QUEUE 08/27/11 19:21:57 CDR WARNING:RQM sbspace ora_ersb is full, Please add the space. e Application log: java.sql.BatchUpdateException: Long transaction aborted.
Possible Cause	When the primary or secondary server is down, data continues to be written to the other server. Data replication happens until the affected server starts running again. Until that point, the data is accumulated in a designated hard disk (in this case, the ora_ersb). When the ora_ersb is full, no more data can be written to the surviving server.
Recommended Action	The only viable action is to bring up the affected node. You could also try to delete some existing data to free up space. See the Considerations for Failure Conditions section in the Cisco MediaSense Installation and Administration Guide. The following two actions will not solve this problem: 1. Disabling replication: currently, Cisco MediaSense does not have a CLI for this action. 2. Adding more space to ora_ersb requires root access and Database Administrator privileges.
Release	Release 8.5(3).
Associated CDETS #	None.