

A Call Placed from an Analog Phone on an FXS Port Fails

| | |
|---------------------------|--|
| Problem Summary | A call placed from an analog phone on an FXS port does not appear to trigger the new_call.vxml application. |
| Error Message | None. |
| Possible Cause | There is no application session command defined on the POTS dial-peer for the telephone's voice port. Note: This command is necessary to enable phones on FXS ports to run a VXML Server script. |
| Recommended Action | On the POTS dial-peer, model your configuration after the following: dial-peer voice 1000 pots application session destination-pattern 12016881000 port 1/0/0 |
| Release | Release 7.0(2) |
| Associated CDETS # | None. |