

A Call Placed from an Analog Phone on an FXS Port Fails

Problem Summary	A call placed from an analog phone on an FXS port does not appear to trigger the new_call.vxml application.
Error Message	None.
Possible Cause	There is no application session command defined on the POTS dial-peer for the telephone's voice port. Note: This command is necessary to enable phones on FXS ports to run a VXML Server script.
Recommended Action	On the POTS dial-peer, model your configuration after the following: dial-peer voice 1000 pots application session destination-pattern 12016881000 port 1/0/0
Release	Release 7.0(2)
Associated CDETS #	None.