

**A Call Placed from an Analog Phone on an FXS Port Fails**

<b>Problem Summary</b>	A call placed from an analog phone on an FXS port does not appear to trigger the new_call.vxml application.
<b>Error Message</b>	None.
<b>Possible Cause</b>	There is no application session command defined on the POTS dial-peer for the telephone's voice port. <b>Note:</b> This command is necessary to enable phones on FXS ports to run a VXML Server script.
<b>Recommended Action</b>	On the POTS dial-peer, model your configuration after the following:  dial-peer voice 1000 pots  application session  destination-pattern 12016881000  port 1/0/0
<b>Release</b>	Release 7.0(2)
<b>Associated CDETS #</b>	None.