

## VoiceXML Scripts Fail

<b>Problem Summary</b>	VoiceXML scripts fail with a CALL_ERROR error message.
<b>Error Message</b>	CALL_ERROR; <a href="http://10.8.7.70:8080/CVP/Server?application=HelloWorld">http://10.8.7.70:8080/CVP/Server?application=HelloWorld</a> at line 5: Undeclared ECMAScript variable audium_vxmlLog
<b>Possible Cause</b>	The Cisco Gateway is configured with the 'no http client cookie' statement.
<b>Recommended Action</b>	<p>Enable the HTTP client to send and receive cookies on the Cisco Gateway when using VoiceXML applications by entering the following command:</p> <pre>http client cookie</pre> <p>This command is enabled by default. You do not need to enter it unless you have previously disabled cookie support by using the 'no http client cookie' command. Use the 'show running-config' command to verify the HTTP configuration information. If the defaults are used, HTTP configuration commands are not shown. If changes have been made to the HTTP defaults, the configuration is shown. For example, the following output shows the HTTP client cookie parameter configured to a non-default value:</p> <pre>no http client cookie</pre>
<b>Release</b>	Release 7.0(2)
<b>Associated CDETS #</b>	None.