

**Main page:** [Cisco Unified MeetingPlace, Release 7.0](#)

**Up one level:** [Planning Your Deployment](#)

**Note:** This section describes audio deployments that do not use video. If you want to use video in your audio deployment, see the [About Audio Deployment Models with Video for Cisco Unified MeetingPlace Release 7.0](#).

Cisco Unified MeetingPlace Release 7.0 uses only SIP signalling.

The system has two audio-only deployment options and both use Cisco Unified Communications Manager to support MGCP (Media Gateway Control Protocol), H.323, SCCP, and SIP gateways.

**Note:** Cisco Unified MeetingPlace Release 7.0 interoperates with all third-party, standards-based IP PBXs; however, only deployments with Cisco Unified Communications Manager have been tested.

## Contents

- [1 Determining which Audio Deployment without Video to Use](#)
- [2 Option 1: Audio Deployment Using Cisco Unified Communications Manager Release 6.1\(2\)](#)
  - ◆ [2.1 Example 1](#)
  - ◆ [2.2 Example 2](#)
  - ◆ [2.3 Example 3](#)
  - ◆ [2.4 Example 4](#)
- [3 Option 2: Audio Deployment Using Cisco Unified Communications Manager Release 6.0\(x\)](#)

## Determining which Audio Deployment without Video to Use

Feature	Option 1: Using Cisco Unified Communications Manager Release 6.1(2)	Option 2: Using Cisco Unified Communications Manager Release 6.0(x)
Directory synchronization	X	
Can use any endpoints	X	
Seamless integration with Cisco Unified MeetingPlace	X	
Already have Cisco Unified Communications Manager Release 6.0(x) and do not want to upgrade		X
System uses audio only and no video		X

## **Option 1: Audio Deployment Using Cisco Unified Communications Manager Release 6.1(2)**

**Note:** Cisco Unified Communications Manager Release 6.1(2) refers to Release 6.1(2.1000-13).

Cisco Unified Communications Manager Release 6.1(2) is the preferred deployment choice in all cases for both audio-only and audio-video. It is required if you want directory synchronization. Using Cisco Unified Communications Manager Release 6.1(2) does not limit your endpoint choices in any way. Video terminals may connect to Cisco Unified MeetingPlace; however, the connection is audio only.

1. SIP or SCCP voice or video
2. Cisco Unified Communications Manager Release 6.1.2
3. SIP
4. Cisco Unified MeetingPlace

Cisco Unified MeetingPlace supports all devices that are supported by Cisco Unified Communications Manager, including the following examples:

### **Example 1**

1. Phone
2. PSTN
3. IOS gateway
4. Cisco Unified Communications Manager Release 6.x
5. Cisco Unified MeetingPlace

### **Example 2**

1. Phone
2. Cisco Unified Communications Manager Release 4.x/5.x
3. H.323 ICT
4. Cisco Unified Communications Manager Release 6.x
5. Cisco Unified MeetingPlace

### **Example 3**

1. Phone
2. Cisco Unified Communications Manager Release 5.x
3. SIP ICT
4. Cisco Unified Communications Manager Release 6.x
5. Cisco Unified MeetingPlace

#### Example 4

1. Video terminal
2. IOS Gatekeeper
3. Cisco Unified Communications Manager Release 6.1.2
4. Cisco Unified MeetingPlace

## **Option 2: Audio Deployment Using Cisco Unified Communications Manager Release 6.0(x)**

**Note:** Cisco Unified Communications Manager Release 6.0(x) refers to Release 6.0(1.2000-3).

Option 1, which uses Cisco Unified Communications Manager Release 6.1(2), is the preferred audio option; however, you can use option 2, which uses Cisco Unified Communications Manager Release 6.0(x), to remain compatible with existing installations, if you do not want to upgrade to Cisco Unified Communications Manager Release 6.1(2).

For deployments that already use Cisco Unified Communications Manager Release 6.0(x), we recommend putting a Cisco Unified Communications Manager Release 6.1(2) cluster in between the older Cisco Unified Communications Manager and Cisco Unified MeetingPlace Release 7.0.

The workflow is shown below.

1. Cisco Unified Communications Manager Release 6.0(x)
2. SIP
3. Cisco Unified MeetingPlace