

Main page: [Cisco Unified MeetingPlace, Release 7.0](#)

Up one level: [Configuration](#)

The Direct Inward Dial (DID) feature enables users to call directly into a meeting by dialing the meeting ID, instead of dialing one of the Cisco Unified MeetingPlace access phone numbers on the [Usage Configuration Page](#).

Contents

- [1 Before You Begin](#)
- [2 Restrictions](#)
- [3 Procedure](#)
- [4 Related Topics](#)

Before You Begin

Configure your call-control device to route DID calls to the Application Server.

For example, in Cisco Unified Communications Manager, configure a route pattern for each meeting ID that you want to make available for DID. Configure these route patterns to send calls to the trunk that leads to the Cisco Unified MeetingPlace Application Server. See [Configuring Call Control for Cisco Unified MeetingPlace](#).

Restrictions

- Beginning in Release 7.0.2, DID callers can join meetings as profiled users through the auto attend feature. If, however, the [Auto attend mode](#) user profile field is set to None, the DID caller can join meetings only as a guest.
- In Release 7.0.1, all DID callers join meetings as guests.

Procedure

1. Log in to the Administration Center.
2. Click **System Configuration > Usage Configuration**.
3. Set the [Route calls to meeting ID that matches DID](#) field to Yes.
4. Click **Save**.

Related Topics

- [Table: Field Reference: Usage Configuration Page](#)
- [Configuring the Auto Attend Feature for Cisco Unified MeetingPlace](#)