

Main page: [Cisco Unified MeetingPlace, Release 7.0](#)

Up one level: [Maintenance Page](#)

Contents

- [1 Adding or Editing SNMP Community Strings](#)
 - ◆ [1.1 Restriction](#)
 - ◇ [1.1.1 Before You Begin](#)
 - ◇ [1.1.2 Procedure](#)
 - ◇ [1.1.3 Related Topics](#)
- [2 Displaying or Deleting SNMP Community Strings](#)
 - ◆ [2.1 Restrictions](#)
 - ◆ [2.2 Procedure](#)
 - ◆ [2.3 Related Topics](#)
- [3 Adding or Editing SNMP Notification Destinations](#)
 - ◆ [3.1 Procedure](#)
 - ◆ [3.2 Related Topics](#)
- [4 Displaying or Deleting SNMP Notification Destinations](#)
 - ◆ [4.1 Procedure](#)
 - ◆ [4.2 Related Topics](#)

Adding or Editing SNMP Community Strings

Restriction

Do not disable the the default community string, which is called meetingplace-public. Doing so will cause the Application Server to give an SNMP "authentication failure" trap every second.

Before You Begin

See [Requirements for SNMP](#).

Procedure

1. Log in to the Administration Center.
2. Click **Maintenance > SNMP > Community Strings**.
3. Click **Add New** or click an existing entry.

4. Enter or change values in the fields.
5. Click **Save**.

Related Topics

- [Table: Field Reference: Add SNMP Community String Page and Edit SNMP Community String Page](#)

Displaying or Deleting SNMP Community Strings

Restrictions

- You cannot delete the default community string, which is called meetingplace-public.
- Do not disable the the default community string, which is called meetingplace-public. Doing so will cause the Application Server to give an SNMP "authentication failure" trap every second.

Procedure

1. Log in to the Administration Center.
2. Click **Maintenance > SNMP > Community Strings**.
3. Check the check box next to each community string that you want to delete, or check the topmost check box to select *all* community strings.
4. Click **Delete Selected**.
5. Click **OK**.

Related Topics

- [Table: Fields Reference: Community Strings Page](#)

Adding or Editing SNMP Notification Destinations

The system sends a message to the IP address specified in the notification destination whenever a trap or inform condition occurs. A trap reports certain events while an inform condition allows one network management application to send trap information to another.

Procedure

1. Log in to the Administration Center.
2. Click **Maintenance > SNMP > Notification Destinations**.
3. Click **Add New** or click an existing entry.

4. Enter or change the values in the fields.
5. Click **Save**.

Related Topics

- [Table: Field Reference: Add SNMP Notification Destination Page and Edit SNMP Notification Destination Page](#)

Displaying or Deleting SNMP Notification Destinations

Procedure

1. Log in to the Administration Center.
2. Click **Maintenance > SNMP > Notification Destinations**.
3. Check the check box next to each notification destination that you want to delete, or check the topmost check box to select *all* notification destinations.
4. Click **Delete Selected**.
5. Click **OK**.

Related Topics

- [Table: Field Reference: Notification Destinations Page](#)