

The following examples are typical translation tables for a customer with two port groups, one connected to a PBX (port group 0) and the second port group (port group 1) connected to a Central Office.

- [Example 1: Port Group 1, PBX](#)
- [Example 2: Port Group 1, Central Office, No Flash or Positive Answer Supervision](#)

## Example 1: Port Group 1, PBX

Port group 0 connected to the PBX.

| From            | To      | Port Group | DestType | Comment  |
|-----------------|---------|------------|----------|--|
| 0\{R?}          | 200\1   | 0          | GENERIC  | Call the company attendant. If a wait for answer is requested, include it at the end.  |
| !\{R?}          | !,200\1 | 0          | GENERIC  | Allow all flash transfers. Wait two seconds after a flash transfer before dialing. If a wait for answer is requested, include it at the end. |
| 2..R?           | \0      | ANYGROUP   | GENERIC  | Allow calls to all internal extensions with and without waiting for an answer. Can use any port in any port group.                           |
| !\{2..R?}       | !,\1    | 0          | GENERIC  | Allow all flash transfers to internal extensions. Add a four second delay after a flash transfer before dialing.                             |
| 9,*011.*        | 0       | BLOCK      | GENERIC  | Block all international calls.   |
| 9,*10.*         | 0       | BLOCK      | GENERIC  | Block all calls using a long distance carrier.   |
| 9,*1?900.*      | 0       | BLOCK      | GENERIC  | Block all calls to the 900 area code.  |
| 9,*1?976.*      | 0       | BLOCK      | GENERIC  | Block all calls to the 976 area code or office code.   |
| 9,*1?...976.... | 0       | BLOCK      | GENERIC  | Block all calls to the 976 office code regardless of the area code.  |
| 9,*1?.....R?    | \0      | 0          | GENERIC  | Accept all calls to the local area code.   |
| 9,*1?.....R?    | \0      | 0          | GENERIC  | Accept all calls to all area codes.  |

## Example 2: Port Group 1, Central Office, No Flash or Positive Answer Supervision

Port group 1 is connected to the Central Office. No flash (making the phone go on and off hook fast) is allowed on port group 1. No positive answer supervision.

| From | To | Port Group | DestType | Comment |
|------|----|------------|----------|---------|
|------|----|------------|----------|---------|

Cisco\_Unified\_MeetingPlace\_Release\_6.1\_-\_Translation\_Table\_Examples

|              |            |       |         |   |
|--------------|------------|-------|---------|---|
| 0R           | 9887200R,, | 1     | GENERIC | Call the company attendant. Ports in group 1 do not have positive answer supervision, so wait four seconds before playing the first prompt. |
| 0            | 9887200    | 1     | GENERIC | Call the company attendant. Do not wait four seconds before playing the first prompt.   |
| 2..R         | 9887\0,,   | 1     | GENERIC | Call local extensions when going over the network. Wait four seconds before playing the first prompt.                                       |
| 2..          | 9887\0     | 1     | GENERIC | Call local extensions when going over the network. Do not wait four seconds before playing the first prompt.                                |
| 011.*        | 0          | BLOCK | GENERIC | Block all international calls.  |
| 10.*         | 0          | BLOCK | GENERIC | Block all calls using a long distance carrier.  |
| 1?900        | 0          | BLOCK | GENERIC | Block all calls to the 900 area code.   |
| 1?976.*      | 0          | BLOCK | GENERIC | Block all calls to the 976 area code or office code.  |
| 1?...976.... | 0          | BLOCK | GENERIC | Block all calls to the 976 office code regardless of the area code.   |
| 1?.....R     | \0,,       | 1     | GENERIC | Accept all calls to the local area code. Wait four seconds before playing the first prompt.   |
| 1?.....      | \0         | 1     | GENERIC | Accept all calls to the local area code.  |
| 1?212.....R  | \0,,       | 1     | GENERIC | Accept calls only to the 212 area code. Wait four seconds before playing the first prompt.  |
| 1?212.....   | \0         | 1     | GENERIC | Accept calls to the 212 area code.  |