

Contents

- [1 Information about Unity Connection Virtualized Deployments](#)
- [2 OVA Downloads](#)
- [3 UCS E blade support matrix with Cisco Unity Connection](#)
- [4 UCS E blade support matrix with Cisco Unity Connection SRSV](#)

Information about Unity Connection Virtualized Deployments

See [Unified Communications in a Virtualized Environment](#).

OVA Downloads

Go to: [OVA Download Location for Unity Connection](#) . Select Products->Cisco Unity Connection->Cisco Unity Connection Virtualization

UCS E blade support matrix with Cisco Unity Connection

| Hardware | Unity Connection 9.1(2) | Unity Connection 10.5(2) | Unity Connection 11.0 |
|---|--|--|---|
| SRE-910 | <ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - - CUC_SRE_9.1_xxx.ova | <ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_10.5.2_100_user_vmv8_v10.ova | <ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_11.0_100_user_xxx.ova |
| Cisco UCS E140S(M1 & M2) (Single-Wide Blade) | <ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA | <ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_10.5.2_100_user_vmv8_v10.ova | <ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_11.0_100_user_xxx.ova |

Cisco_Unity_Connection_on_UCSE

| | | | |
|---|---|--|--|
| | - CUC_SRE_9.1_xxx.ova | | |
| <u>Cisco UCS E140D, E140DP, E160D, and E160DP</u> (Double-Wide Blades) | <ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_SRE_9.1_xxx.ova | <ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_10.5.2_100_user_vmv8_v10.ova | <ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_11.0_100_user_xxx.ova |
| <u>Cisco UCS E160D-M2, E180D-M2</u> (Double-Wide Blades) | <ul style="list-style-type: none"> • 150 Voicemail users • 1 vCPU (1.8GHz) Supported OVA - CUC_SRE_9.1_xxx.ova (for Voice mail only functionality) OR • 2 vCPU (1.8 GHz) Supported OVA - CUC_9.1_xxx.ova (for Integrated and SIB functionality) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions | <ul style="list-style-type: none"> • 150 Voicemail users • 1 vCPU (1.8GHz) Supported OVA - CUC_10.5.2_100_user_xxx.ova (for Voice mail only functionality) OR • 2 vCPU (1.8 GHz) Supported OVA - CUC_10.5.2_xxx.ova (for Integrated and SIB functionality) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions | <ul style="list-style-type: none"> • 200 Voicemail users • 1 vCPU (1.8GHz) Supported OVA - CUC_11.0_100_user_xxx.ova (for Voice mail only functionality) OR • 2 vCPU (1.8 GHz) Supported OVA - CUC_11.0_xxx.ova (for Integrated and SIB functionality) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions |

UCS E blade support matrix with Cisco Unity Connection SRSV

| Hardware | Unity Connection 9.1(2) | Unity Connection 10.5(2) | Unity Connection 11.0 | Unity Connection 11.5 |
|----------|-------------------------|--------------------------|-----------------------|-----------------------|
|----------|-------------------------|--------------------------|-----------------------|-----------------------|

Cisco_Unity_Connection_on_UCSE

| | | | | |
|---|--|--|--|--|
| <p><u>SRE-910</u></p> | <ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_9.1_xxx.oiva | <ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_10.5.2_xxx.oiva | <ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_11.0_xxx.oiva | <ul style="list-style-type: none"> • 500 V only u • 1 vCP • 4 GB • 160 G pre-al partiti • Suppo CUCS |
| <p><u>Cisco UCS E140S(M1 & M2)</u> (Single-Wide Blade)</p> | <ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_9.1_xxx.oiva | <ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_10.5.2_xxx.oiva | <ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_11.0_xxx.oiva | <ul style="list-style-type: none"> • 500 V only u • 1 vCP • 4 GB • 160 G pre-al partiti • Suppo CUCS |
| <p><u>Cisco UCS E140D, E140DP, E160D, and E160DP</u> (Double-Wide Blades)</p> | <ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_9.1_xxx.oiva | <ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_10.5.2_xxx.oiva | <ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_11.0_xxx.oiva | <ul style="list-style-type: none"> • 500 V only u • 1 vCP • 4 GB • 160 G pre-al partiti • Suppo CUCS |
| <p><u>Cisco UCS E160D-M2, E180D-M2</u> (Double-Wide Blades)</p> | <ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions | <ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions | <ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions | <ul style="list-style-type: none"> • 500 V only u • 1 vCP • 4 GB • 160 G pre-al partiti |

Cisco_Unity_Connection_on_UCSE

- Supported OVA -
OVA

-CUCSRSV_9.1_xxx.ova

- Supported OVA -
OVA

-CUCSRSV_10.5.2_xxx.ova

- Supported OVA -
OVA

-CUCSRSV_11.0_xxx.ova

- Supported OVA -
OVA

-CUCSRSV_xxx.ova

Back to: [Unified Communications in a Virtualized Environment](#)