

Contents

- [1 Information about Unity Connection Virtualized Deployments](#)
- [2 OVA Downloads](#)
- [3 UCS E blade support matrix with Cisco Unity Connection](#)
- [4 UCS E blade support matrix with Cisco Unity Connection SRSV](#)

Information about Unity Connection Virtualized Deployments

See [Unified Communications in a Virtualized Environment](#).

OVA Downloads

Go to: [OVA Download Location for Unity Connection](#) . Select Products->Cisco Unity Connection->Cisco Unity Connection Virtualization

UCS E blade support matrix with Cisco Unity Connection

Hardware	Unity Connection 9.1(2)	Unity Connection 10.5(2)	Unity Connection 11.0
SRE-910	<ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - - CUC_SRE_9.1_xxx.ova 	<ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_10.5.2_100_user_vmv8_v10.ova 	<ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_11.0_100_user_xxx.ova
Cisco UCS E140S(M1 & M2) (Single-Wide Blade)	<ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA 	<ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_10.5.2_100_user_vmv8_v10.ova 	<ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_11.0_100_user_xxx.ova

Cisco_Unity_Connection_on_UCSE

	- CUC_SRE_9.1_xxx.ova		
<u>Cisco UCS E140D, E140DP, E160D, and E160DP</u> (Double-Wide Blades)	<ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_SRE_9.1_xxx.ova 	<ul style="list-style-type: none"> • 150 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_10.5.2_100_user_vmv8_v10.ova 	<ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - CUC_11.0_100_user_xxx.ova
<u>Cisco UCS E160D-M2, E180D-M2</u> (Double-Wide Blades)	<ul style="list-style-type: none"> • 150 Voicemail users • 1 vCPU (1.8GHz) Supported OVA - CUC_SRE_9.1_xxx.ova (for Voice mail only functionality) OR • 2 vCPU (1.8 GHz) Supported OVA - CUC_9.1_xxx.ova (for Integrated and SIB functionality) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions 	<ul style="list-style-type: none"> • 150 Voicemail users • 1 vCPU (1.8GHz) Supported OVA - CUC_10.5.2_100_user_xxx.ova (for Voice mail only functionality) OR • 2 vCPU (1.8 GHz) Supported OVA - CUC_10.5.2_xxx.ova (for Integrated and SIB functionality) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions 	<ul style="list-style-type: none"> • 200 Voicemail users • 1 vCPU (1.8GHz) Supported OVA - CUC_11.0_100_user_xxx.ova (for Voice mail only functionality) OR • 2 vCPU (1.8 GHz) Supported OVA - CUC_11.0_xxx.ova (for Integrated and SIB functionality) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions

UCS E blade support matrix with Cisco Unity Connection SRSV

Hardware	Unity Connection 9.1(2)	Unity Connection 10.5(2)	Unity Connection 11.0	Unity Connection 11.5
----------	-------------------------	--------------------------	-----------------------	-----------------------

Cisco_Unity_Connection_on_UCSE

<p><u>SRE-910</u></p>	<ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_9.1_xxx.o 	<ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_10.5.2_xxx.o 	<ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_11.0_xxx.o 	<ul style="list-style-type: none"> • 500 V only u • 1 vCP • 4 GB • 160 G pre-al partiti • Suppo CUCS
<p><u>Cisco UCS E140S(M1 & M2)</u> (Single-Wide Blade)</p>	<ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_9.1_xxx.o 	<ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_10.5.2_xxx.o 	<ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_11.0_xxx.o 	<ul style="list-style-type: none"> • 500 V only u • 1 vCP • 4 GB • 160 G pre-al partiti • Suppo CUCS
<p><u>Cisco UCS E140D, E140DP, E160D, and E160DP</u> (Double-Wide Blades)</p>	<ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_9.1_xxx.o 	<ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_10.5.2_xxx.o 	<ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions • Supported OVA - OVA -CUCRSRV_11.0_xxx.o 	<ul style="list-style-type: none"> • 500 V only u • 1 vCP • 4 GB • 160 G pre-al partiti • Suppo CUCS
<p><u>Cisco UCS E160D-M2, E180D-M2</u> (Double-Wide Blades)</p>	<ul style="list-style-type: none"> • 200 Voicemail only users • 1 vCPU (1.8GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions 	<ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions 	<ul style="list-style-type: none"> • 500 Voicemail only users • 1 vCPU (1.8 GHz) • 4 GB RAM • 160 GB Disk with pre-aligned disk partitions 	<ul style="list-style-type: none"> • 500 V only u • 1 vCP • 4 GB • 160 G pre-al partiti

Cisco_Unity_Connection_on_UCSE

- Supported OVA -
OVA

-CUCSRSV_9.1_xxx.ova

- Supported OVA -
OVA

-CUCSRSV_10.5.2_xxx.ova

- Supported OVA -
OVA

-CUCSRSV_11.0_xxx.ova

- Supported OVA -
OVA

-CUCSRSV_xxx.ova

Back to: [Unified Communications in a Virtualized Environment](#)